Asymptotic Behavior: Isolated Zero

The magnitude response is simple at low and high frequencies.

$H(j\omega) = j\omega - z_1$



Asymptotic Behavior: Isolated Zero

Two asymptotes provide a good approxmation on log-log axes.

$H(s) = s - z_1$



$$\lim_{\omega\to 0} |H(j\omega)| = z_1$$

$$\lim_{\omega\to\infty} |H(j\omega)| = \omega$$

Asymptotic Behavior: Isolated Pole

The magnitude response is simple at low and high frequencies.

$H(s) = \frac{9}{s-p_1}$



Asymptotic Behavior: Isolated Pole

Two asymptotes provide a good approxmation on log-log axes.

$H(s) = \frac{9}{s-p_1}$



$$\lim_{\omega\to 0} |H(j\omega)| = \frac{9}{p_1}$$

$$\lim_{\omega\to\infty} |H(j\omega)| = \frac{9}{\omega}$$

Check Yourself

Compare log-log plots of the frequency-response magnitudes of the following system functions:

$H_1(s) = \frac{1}{s+1}$ and $H_2(s) = \frac{1}{s+10}$

The former can be transformed into the latter by

1. shifting horizontally
2. shifting and scaling horizontally
3. shifting both horizontally and vertically
4. shifting and scaling both horizontally and vertically
5. none of the above

Check Yourself

Compare log-log plots of the frequency-response magnitudes of the following system functions:

$H_1(s) = \frac{1}{s+1}$ and $H_2(s) = \frac{1}{s+10}$



Check Yourself

Compare log-log plots of the frequency-response magnitudes of the following system functions:

$H_1(s) = \frac{1}{s+1}$ and $H_2(s) = \frac{1}{s+10}$

The former can be transformed into the latter by 3

1. shifting horizontally
2. shifting and scaling horizontally
3. shifting both horizontally and vertically
4. shifting and scaling both horizontally and vertically
5. none of the above

no scaling in either vertical or horizontal directions!

Asymptotic Behavior of More Complicated Systems

Constructing $H(s_0)$.

$$H(s_0) = K\frac{\prod_{q=1}^{Q}(s_0-z_q)}{\prod_{p=1}^{P}(s_0-p_p)} \quad \begin{array}{l}\leftarrow \text{product of vectors for zeros}\\ \leftarrow \text{product of vectors for poles}\end{array}$$



Asymptotic Behavior of More Complicated Systems

The magnitude of a product is the product of the magnitudes.

$$|H(s_0)| = \left|K\frac{\prod_{q=1}^{Q}(s_0-z_q)}{\prod_{p=1}^{P}(s_0-p_p)}\right| = |K|\frac{\prod_{q=1}^{Q}|s_0-z_q|}{\prod_{p=1}^{P}|s_0-p_p|}$$



Bode Plot

The log of the magnitude is a sum of logs.

$$|H(s_0)| = \left|K\frac{\prod_{q=1}^{Q}(s_0-z_q)}{\prod_{p=1}^{P}(s_0-p_p)}\right| = |K|\frac{\prod_{q=1}^{Q}|s_0-z_q|}{\prod_{p=1}^{P}|s_0-p_p|}$$

$$\log|H(j\omega)| = \log|K| + \sum_{q=1}^{Q}\log|j\omega-z_q| - \sum_{p=1}^{P}\log|j\omega-p_p|$$

Bode Plot: Adding Instead of Multiplying

$H(s) = \frac{s}{(s+1)(s+10)}$



Bode Plot: Adding Instead of Multiplying

$H(s) = \frac{s}{(s+1)(s+10)}$



Bode Plot: Adding Instead of Multiplying

$H(s) = \frac{s}{(s+1)(s+10)}$



Bode Plot: Adding Instead of Multiplying

$H(s) = \frac{s}{(s+1)(s+10)}$



Asymptotic Behavior: Isolated Zero

The angle response is simple at low and high frequencies.

$H(s) = s - z_1$



Asymptotic Behavior: Isolated Zero

Three straight lines provide a good approxmation on log-log axes

$H(s) = s - z_1$



$$\lim_{\omega\to 0} \angle H(j\omega) = 0$$

$$\lim_{\omega\to\infty} \angle H(j\omega) = \pi/2$$

Asymptotic Behavior: Isolated Pole

The angle response is simple at low and high frequencies.

$H(s) = \frac{9}{s-p_1}$



Asymptotic Behavior: Isolated Pole

Three straight lines provide a good approxmation on log-log axes

$H(s) = \frac{9}{s-p_1}$



$$\lim_{\omega\to 0} \angle H(j\omega) = 0$$

$$\lim_{\omega\to\infty} \angle H(j\omega) = -\pi/2$$

Bode Plot

The angle of a product is the sum of the angles.

$$\angle H(s_0) = \angle\left(K\frac{\prod_{q=1}^{Q}(s_0-z_q)}{\prod_{p=1}^{P}(s_0-p_p)}\right) = \angle K + \sum_{q=1}^{Q}\angle(s_0-z_q) - \sum_{p=1}^{P}\angle(s_0-p_p)$$



The angle of K can be 0 or π for systems described by linear differential equations with constant, real-valued coefficients.

Bode Plot

$H(s) = \frac{s}{(s+1)(s+10)}$



Bode Plot

$H(s) = \frac{s}{(s+1)(s+10)}$



Bode Plot

$H(s) = \frac{s}{(s+1)(s+10)}$



Bode Plot

$H(s) = \frac{s}{(s+1)(s+10)}$



From Frequency Response to Bode Plot

The magnitude of $H(j\omega)$ is a product of magnitudes.

$$|H(j\omega)| = |K|\frac{\prod_{q=1}^{Q}|j\omega-z_q|}{\prod_{p=1}^{P}|j\omega-p_p|}$$

The log of the magnitude is a sum of logs.

$$\log|H(j\omega)| = \log|K| + \sum_{q=1}^{Q}\log|j\omega-z_q| - \sum_{p=1}^{P}\log|j\omega-p_p|$$

The angle of $H(j\omega)$ is a sum of angles.

$$\angle H(j\omega) = \angle K + \sum_{q=1}^{Q}\angle(j\omega-z_q) - \sum_{p=1}^{P}\angle(j\omega-p_p)$$

Check Yourself



Which corresponds to the Bode approximation above?

1. $\frac{1}{(s+1)(s+10)(s+100)}$
2. $\frac{s+1}{(s+10)(s+100)}$
3. $\frac{(s+10)(s+100)}{s+1}$
4. $\frac{s+100}{(s+1)(s+10)}$
5. none of the above

Check Yourself



Which corresponds to the Bode approximation above? 2

1. $\frac{1}{(s+1)(s+10)(s+100)}$
2. $\frac{s+1}{(s+10)(s+100)}$
3. $\frac{(s+10)(s+100)}{s+1}$
4. $\frac{s+100}{(s+1)(s+10)}$
5. none of the above

Bode Plot: dB

$H(s) = \frac{10s}{(s+1)(s+10)}$



Bode Plot: dB

$H(s) = \frac{10s}{(s+1)(s+10)}$



Bode Plot: dB

$H(s) = \frac{10s}{(s+1)(s+10)}$



Bode Plot: dB

$H(s) = \frac{10s}{(s+1)(s+10)}$



Bode Plot: Accuracy

The straight-line approximations are surprisingly accurate.



X	$20\log_{10}X$
1	0 dB
$\sqrt{2}$	≈ 3 dB
2	≈ 6 dB
10	20 dB
100	40 dB

Check Yourself

Could the phase plots of any of these systems be equal to each other? [caution: this is a trick question]



Check Yourself



Check Yourself



Check Yourself

Could the phase plots of any of these systems be equal to each other? [caution: this is a trick question] yes



phase of 2 could be same as phase of 3: depends on sign of K

Frequency Response of a High-Q System

The frequency-response magnitude of a high-Q system is peaked.

$$H(s) = \frac{1}{1+\frac{1}{Q}\frac{s}{\omega_0}+\left(\frac{s}{\omega_0}\right)^2}$$



Frequency Response of a High-Q System

The frequency-response magnitude of a high-Q system is peaked.

$$H(s) = \frac{1}{1+\frac{1}{Q}\frac{s}{\omega_0}+\left(\frac{s}{\omega_0}\right)^2}$$



Frequency Response of a High-Q System

The frequency-response magnitude of a high-Q system is peaked.

$$H(s) = \frac{1}{1+\frac{1}{Q}\frac{s}{\omega_0}+\left(\frac{s}{\omega_0}\right)^2}$$



Frequency Response of a High-Q System

The frequency-response magnitude of a high-Q system is peaked.

$$H(s) = \frac{1}{1+\frac{1}{Q}\frac{s}{\omega_0}+\left(\frac{s}{\omega_0}\right)^2}$$



Frequency Response of a High-Q System

The frequency-response magnitude of a high-Q system is peaked.

$$H(s) = \frac{1}{1+\frac{1}{Q}\frac{s}{\omega_0}+\left(\frac{s}{\omega_0}\right)^2}$$



Check Yourself

Find dependence of peak magnitude on Q (assume $Q > 3$).

$$H(s) = \frac{1}{1+\frac{1}{Q}\frac{s}{\omega_0}+\left(\frac{s}{\omega_0}\right)^2}$$



Check Yourself

Find dependence of peak magnitude on Q (assume $Q > 3$).

Analyze with vectors.

low frequencies high frequencies



Peak magnitude increases with Q!

Frequency Response of a High-Q System

As Q increases, the width of the peak narrows.

$$H(s) = \frac{1}{1+\frac{1}{Q}\frac{s}{\omega_0}+\left(\frac{s}{\omega_0}\right)^2}$$



Frequency Response of a High-Q System

As Q increases, the width of the peak narrows.

$$H(s) = \frac{1}{1+\frac{1}{Q}\frac{s}{\omega_0}+\left(\frac{s}{\omega_0}\right)^2}$$



Frequency Response of a High-Q System

As Q increases, the width of the peak narrows.

$$H(s) = \frac{1}{1+\frac{1}{Q}\frac{s}{\omega_0}+\left(\frac{s}{\omega_0}\right)^2}$$



Frequency Response of a High-Q System

As Q increases, the width of the peak narrows.

$$H(s) = \frac{1}{1+\frac{1}{Q}\frac{s}{\omega_0}+\left(\frac{s}{\omega_0}\right)^2}$$



Frequency Response of a High-Q System

As Q increases, the width of the peak narrows.

$$H(s) = \frac{1}{1+\frac{1}{Q}\frac{s}{\omega_0}+\left(\frac{s}{\omega_0}\right)^2}$$



Check Yourself

Estimate the "3dB bandwidth" of the peak (assume $Q > 3$).

Let ω_l (or ω_h) represent the lowest (or highest) frequency for which the magnitude is greater than the peak value divided by $\sqrt{2}$. The 3dB bandwidth is then $\omega_h - \omega_l$.



Check Yourself

Estimate the "3dB bandwidth" of the peak (assume $Q > 3$).

Analyze with vectors.

low frequencies high frequencies



Bandwidth approximately $\frac{1}{Q}$

Frequency Response of a High-Q System

As Q increases, the phase changes more abruptly with ω.

$$H(s) = \frac{1}{1+\frac{1}{Q}\frac{s}{\omega_0}+\left(\frac{s}{\omega_0}\right)^2}$$



Frequency Response of a High-Q System

As Q increases, the phase changes more abruptly with ω.

$$H(s) = \frac{1}{1+\frac{1}{Q}\frac{s}{\omega_0}+\left(\frac{s}{\omega_0}\right)^2}$$



Frequency Response of a High-Q System

As Q increases, the phase changes more abruptly with ω.

$$H(s) = \frac{1}{1+\frac{1}{Q}\frac{s}{\omega_0}+\left(\frac{s}{\omega_0}\right)^2}$$



Frequency Response of a High-Q System

As Q increases, the phase changes more abruptly with ω.

$$H(s) = \frac{1}{1+\frac{1}{Q}\frac{s}{\omega_0}+\left(\frac{s}{\omega_0}\right)^2}$$



Frequency Response of a High-Q System

As Q increases, the phase changes more abruptly with ω.

$$H(s) = \frac{1}{1+\frac{1}{Q}\frac{s}{\omega_0}+\left(\frac{s}{\omega_0}\right)^2}$$



Check Yourself

Estimate change in phase that occurs over the 3dB bandwidth.

$$H(s) = \frac{1}{1+\frac{1}{Q}\frac{s}{\omega_0}+\left(\frac{s}{\omega_0}\right)^2}$$



Check Yourself

Estimate change in phase that occurs over the 3dB bandwidth.

Analyze with vectors.

low frequencies high frequencies



Change in phase approximately $\frac{\pi}{2}$.